INSTALLATION INSTRUCTIONS

Item#N6552-690 (New. 2021/05/10)

READ AND SAVE THESE INSTRUCTIONS

WARNING! SHUT POWER OFF AT FUSE OR CIRCUIT BREAKER.

AVERTISSEMENT! COUPER LE COURANT AU NIVEAU DES FUSIBLES OU DU DISJONCTEUR.

HANGING THE FIXTURE (Fig. 1)

- Shut off power at the fuse box or circuit breaker box and remove the old fixture including the mounting hardware.
- Carefully unpack your new fixture and lay out all the parts in a clear area. Take care not to misplace any small parts necessary for installation.
- 3. Place plastic washer (G) over all thread (I). Then thread rod (H) to all thread (I).
- 4. Place plastic washer (G), cloth shade (F) and plastic washer (G) over all thread of rod (H). Then thread the canopy (D) to the rod (H). Carefully pass the wires through each part's during assembly.
- Place candle covers (K) over sockets (N) of fixture body.
- Install (4) four candelabra base bulbs (J) up to 60 watts each or CFL or LED equivalent (not included) in accordance with the fixture specification. —DO NOT EXCEED THE MAXIMUM WATTAGE RATING! (NE PAS DEPASSER LA PUISSANCE NOMINALE MAXIMALE!)
- 7. Thread mounting screws (A) into pre-drilled holes in mounting plate (B), spaced the same distance apart as the holes in canopy (D) and secure with hex nut (L).
- 8. Attach the mounting plate (B) to junction box (not included) using mounting screws (C) (size: #8-32N*L0.5"). The side of circular strap (B) marked "GND" must face out.

CONNECTING THE WIRES (Fig. 2)

9. Connect the electrical wires as shown in figure 2, making sure that all wire connectors are secured. If your junction box has a ground wire (green or bare copper), connect the fixture's ground wire to it. Otherwise, connect the fixture's ground wire directly to the mounting plate (B) using the green screw provided. After wires are connected, tuck them carefully into junction box.

COMPLETING THE INSTALLATION (Fig. 1)

- 10. Align the canopy (D) to the mounting screws (A) and secure it with cap nuts (E).
- 11. Attach crystal drop (M) on finial (O).

Your installation is now complete. Return power to the junction box and test the fixture.

Note: Illustration (Fig.1) on this manual is for installation purposes only. It may or may not be identical to the fixture purchased.





